
Yealink VCM35 Pro Datasheet

Introduction

The Yealink VCM35 Pro is an innovative video conferencing microphone designed to accommodate various meeting room needs. The VCM35 Pro features a built-in 6+1 microphone array with an optimal voice pickup radius of 3 m and 360° voice pickup coverage. It supports 360° omnidirectional voice pickup and auxiliary sound source localization*.

Equipped with Yealink's high-quality acoustic echo cancellation and noise suppression technologies, the VCM35 Pro can effectively eliminate up to 90 dB of ambient noise, delivering high-quality audio in full-duplex calls. Its advanced voice pickup technology provides comprehensive audio coverage for meeting rooms of all sizes.

The VCM35 Pro is equipped with two VCH ports that support daisy-chain deployment. It supports multiple installation methods, including tabletop placement, adhesive mounting, and in-table embedded installation. With high scalability and flexibility, it enables fast and convenient deployment to fully cover meeting rooms of various sizes.



HD Hi-Fi Microphone | Yealink Full Duplex Technology | 3m-360° Voice Pickup Range | Star-Cascaded or Daisy-Chain Deployment



Key Features and Benefits

- HD Hi-Fi microphone
- Yealink full-duplex technology
- 3 m radius optimal voice pickup range
- Multiple deployment options
- Star-cascaded and Daisy-chain support

Specifications

Specifications	Description
Microphone Features	• HD Audio

	• Yealink Full Duplex Technology • Yealink Acoustic Echo Cancellation • Yealink Noise Proof Technology • 3 m radius optimal voice pickup range • Muting the microphone with the touchpad • Auxiliary sound source localization* • Can be used as an expansion microphone • Frequency response: 100Hz–20kHz
Physical Features	• Dimension (W × D × H): 110 × 110 × 18 mm • N.W/CTN: 0.261kg • G.W/CTN: 0.306kg • Operating humidity: 10%–90% • Storage temperature: 0°C–40°C (+32°F–104°F)
Package Contents	• VCM35 Pro • RJ45 connector for Ethernet cable • Cable cover • Cable cover screw • Base adhesive • Quick start guide

*Supported in future versions.

Device Compatibility

Room Accessories Compatibility Lists